

P704913

[illegible][illegible][illegible][illegible][illegible][illegible][illegible]

**SIDEWALLS
AS
SEMICONDUCTOR ETCH STOP AND DIFFUSION BARRIER**

CROSS REFERENCE TO RELATED APPLICATIONS

This application is a continuation-in-part of U.S. Patent Application No. 09/712,449 entitled "VERTICAL JUNCTION FIELD EFFECT SEMICONDUCTOR DIODES" filed by Richard A. Metzler on November 13, 2000.

Furthermore, this application is related to U.S. Patent Application No. 09/689,074 entitled "METHOD AND APPARATUS FOR PATTERNING FINE DIMENSIONS" filed by Richard A. Metzler on October 12, 2000 and U.S. Patent Application No. 09/502,026 entitled "METHOD AND APPARATUS FOR CYLINDRICAL SEMICONDUCTOR DIODES" filed by Richard A. Metzler on February 10, 2000.

BACKGROUND OF THE INVENTION

1. Field of the Invention

The invention generally relates to semiconductor devices and fabrication of the same.

2. Background Information

It is desirable to form smaller geometries or dimensions for semiconductor devices for a number of reasons including to decrease manufacturing costs. A smaller semiconductor device uses less area on a wafer so that additional devices can be formed in the same area of a wafer. More dense features allows for more dense devices, such as increased channel width in MOSFETs which leads to lower on resistance. Additionally, by providing finer geometry devices, die size

can be reduced in order to reduce manufacturing costs of devices.

Semiconductor devices of various kinds are well known in the prior art. One semiconductor device that is well known
5 is a semiconductor diode. Semiconductor diodes are widely used in electronic circuits for various purposes. The primary purpose of such semiconductor diodes is to provide conduction of current in a forward direction in response to a forward voltage bias, and to block conduction of current in
10 the reverse direction in response to a reverse voltage bias. This rectifying function is widely used in such circuits as power supplies of various kinds as well as in many other electronic circuits.

In manufacturing semiconductor devices, the fabrication
15 process typically includes etching and diffusion. Etching is a process where material is removed from a substrate, a layer or thin film that was placed on a substrate. Diffusion is a process where a dopant is introduced into a material and diffuses therein as a gradient of the dopant. In either
20 case, a pattern is typically used to selectively etch or diffuse a dopant in areas of a semiconductor wafer for manufacturing semiconductor devices.

Etching can be accomplished by a wet etch process or a dry etch process. A wet etch process typically involves
25 removing exposed material in a wet acid bath. A dry etch process avoids the use of a wet acid bath and typically uses a chemical introduced by a gas under pressure or into a chamber with lower than atmospheric pressure with ions excited by an excitation energy. An etch process which
30 etches a material in all directions at the same rate is said

to be isotropic. An etch process which has a horizontal etch rate that differs from a vertical etch rate for a material is not isotropic but is said to be anisotropic. A lateral etch ratio L_r is defined as the ratio of the etch rate in the horizontal direction to the etch rate in the vertical direction for a give material. $L_r = (\text{Horizontal Etch Rate of Material} / \text{Vertical Etch Rate of Material})$. The degree of anisotropy $A = (1 - L_r)$.

Diffusion can be accomplished by supplying a dopant to the semiconductor material and heating the dopant and the semiconductor material together to diffuse the dopant into the silicon. Supplying the dopant to the semiconductor material can be accomplished by implanting the dopant by ion implantation methods. To complete the diffusion step, the semiconductor material is heated with the implanted dopant to diffuse the dopant into the semiconductor material.

In order to form a pattern of diffusion or to etch a pattern of material, a mask or photoresist material is typically used to protect material that is not to be etched or is not to have a dopant diffused therein and expose material that is to be etched or is to have a dopant diffused therein. Other known methods can be used to protect material as well as expose material to form a pattern for etching and diffusing.

BRIEF SUMMARY OF THE INVENTION

The invention includes methods and apparatus as described in the claims found below.

1. A method of determining the presence of a substance in a sample, comprising the steps of: (a) providing a sample; (b) measuring the amount of the substance in the sample; (c) comparing the measured amount to a predetermined threshold; and (d) determining the presence of the substance in the sample based on the comparison.

BRIEF DESCRIPTION OF THE FIGURES

Figure 1A illustrates a semiconductor wafer with a repetitive pattern.

5 Figure 1B illustrates the semiconductor wafer inserted into a chamber, oven, or other container for etching or diffusion processing to manufacture a semiconductor device.

Figure 1C is a schematic diagram of a semiconductor device which may be manufactured on the semiconductor wafer.

10 Figure 1D is a schematic diagram of a semiconductor device which may be manufactured on the semiconductor wafer.

Figure 1E is a schematic diagram of a semiconductor device which may be manufactured on the semiconductor wafer.

15 Figure 1F is a schematic diagram of a semiconductor device which may be manufactured on the semiconductor wafer.

Figures 2A-2F are cross-sectional views illustrating the steps in one embodiment for forming fine geometric dimensions of a repetitive pattern.

20 Figures 3A-3F are cross-sectional views illustrating steps in an exemplary process for fabricating a diode connected vertical junction field effect device.

Figures 4A-4I are cross-sectional views illustrating steps in another exemplary process for fabricating the diode connected vertical junction field effect device.

25 Figures 5 is a magnified cross-sectional view illustrating four vertical JFED diode structures.

Figures 6A-6C are top views of alternate structures for the vertical JFED diode.

Figures 7A-7B illustrate schematic equivalent circuits for a two dimensional model of an N-channel vertical JFED diode.

Figure 7C illustrates the schematic equivalent circuit for a three dimensional model of the N-channel vertical JFED diode.

Figures 8A-8B illustrate schematic equivalent circuits for a two dimensional model of an P-channel vertical JFED diode.

Figure 8C illustrates the schematic equivalent circuit for a three dimensional model of the P-channel vertical JFED diode.

Figure 9 illustrates active diode areas on a wafer employing a plurality of vertical JFED diodes.

Figure 10 is a schematic diagram of the electrical equivalent of one active diode area.

Figures 11A-11B, 12A-12B, and 13A-13B are top views and cross-section side views illustrating yet another embodiment for forming fine geometric dimensions of a repetitive pattern using sidewalls.

Figures 14-16 are top views of alternate embodiments of geometric shapes having the fine geometric dimensions of a repetitive pattern formed using sidewalls.

Like reference numbers and designations in the drawings indicate like elements providing similar functionality.

DETAILED DESCRIPTION OF THE INVENTION

Methods and apparatus of forming a semiconductor device using pedestals and sidewalls are disclosed. The pedestals and sidewalls may provide an etch stop and/or a diffusion barrier during manufacture of a semiconductor device. Processes of forming diode connected vertical cylindrical field effect devices are disclosed to exemplify the use of the pedestals and/or sidewalls. Systems for forming the pedestals and sidewalls onto a wafer are disclosed.

Referring now to Figure 1A, a semiconductor wafer 100 having a repetitive geometric pattern is illustrated. An exploded view of a portion 101 of the wafer 100 is illustrated as well. The wafer 100 includes a plurality of device areas 102. Each of the device areas 102 includes a repetitive geometric pattern 108 which is patterned in accordance with the invention using semiconductor manufacturing processes and techniques. Scribe channels are defined between device areas 102 in order to separate them after completion of processing the wafer 100. It is understood that there are many device areas 102 on the wafer 100, with only four being shown in Figure 1A. Each individual device area 102 may contain thousands or more or less of the repetitive geometric pattern 108.

Referring now to Figure 1B, the semiconductor wafer 100 during manufacturing may be placed into a chamber, oven, or other container 110 for diffusion or etch processing. The diffusion or etch processing may occur over a pattern. The diffusion or etch processing may be accomplished in the chamber, oven, or other container 110 by using a gas 112, ion implantation 114, a wet chemical 116, a plasma, or other

method of delivering a chemical or ion or a combination thereof.

Referring now to Figures 1C-1F, the invention can be utilized in manufacturing a number of types of devices including semiconductor devices illustrated herein. Figure 1C illustrates a schematic symbol for a diode having an anode (a) and a cathode (c). Figure 1D illustrates a schematic symbol for a junction field effect transistor (JFET) having a gate (g), source (s), and drain (d). Figure 1E illustrates a schematic symbol for a bipolar-junction transistor (BJT) having a base (b), a collector (c), and an emitter (e). Figure 1F illustrates a schematic symbol for an insulated gate field effect transistor (IGFET) having a gate (g), a source (s), and a drain (d). The invention can be utilized to manufacture these and other devices during etching and diffusion of dopants. The invention is particularly well suited to the manufacture of power metal oxide semiconductor field effect transistors (MOSFETs) when used in a repetitive pattern.

Referring now to Figures 2A through 2I, the steps to forming fine geometries using larger mask dimensions is illustrated. In the embodiment depicted in Figures 2A-2F, material1 and material2 are etched independently. In the case of semiconductor processing for example, material1 and material2 can be polysilicon and oxide or oxide and polysilicon respectively in alternate embodiments. In the first steps of the invention, a repetitive pattern of "pedestals" of material1 are formed on the surface of a substrate or a support material. The pedestals as will be further illustrated can be of any shape including circles,

squares, rectangles, bars, etc. The repetitive pattern of pedestals has a cross-section dimension or width and a spacing there between to form a pitch of the repetitive pattern. Either of the width and spacing dimensions can be modified to alter the dimensions of the fine geometries of the end result.

In Figure 2A, material 200 is deposited or grown onto a support member 201. The support member 201 may be a substrate or a backing which facilitates supporting the fine geometries. If the support member 201 is a substrate, it is etched independently of material 1 and material 2. A photoresist 204 is deposited on top of the material 200. A mask 206 having a desired pattern is used to generate a first geometric shape. The dimensions of the repetitive pattern of the desired geometric shape is larger than the desired end result. The end resultant fine geometries of the repetitive pattern has a smaller pitch than ordinarily obtained from the pitch of the mask dimensions.

The mask 206 has a pattern 208 therein which blocks light or other electromagnetic radiation from propagating through areas of the mask 206. Openings 207 in the pattern of the mask 206 exposes the photoresist material 204 to the electromagnetic radiation. After the photoresist 204 is exposed to the electromagnetic radiation, those areas can be then etched away leaving the pattern photoresist 204' on the material 200 as illustrated in Figure 2B. The pattern of photoresist 204' has openings 209 exposing the material 200.

The material 200 which is exposed at openings 209 can be etched away to the support material 201. Preferably

the exposed portions of the material1 layer 200 are etched away by plasma etching so that pedestals 200' will have substantially straight (vertical) sidewalls, as opposed to somewhat tapered sidewalls typically provided by wet etching.

5 After etching, the pattern of photoresist 204' is then removed from the surfaces to generate the patterned pedestals 200' formed from the material1 layer 200 as illustrated in Figure 2C.

10 The repetitive pattern of the pedestals 200' formed out of the layer of material1 establishes the initial pitch (IP). The initial pitch is formed of an initial space (IS) 209' between the pedestals 200' and an initial width (IW) of the pedestals 200'. The initial pitch is the sum of dimension of the initial space IS and the initial width IW. $IP=IS + IW$.
15 In one embodiment, the initial width is 0.3 microns (um) and the initial space is 0.5 um forming an initial pitch of 0.8 um. In another embodiment, the initial width is 0.75 um and the initial space is 1.25 um forming an initial pitch of 2 um. By varying these initial dimensions in the pedestals,
20 other resultant dimensions in fine geometries can be obtained. The repetitive pattern of pedestals 200' becomes a construction element for the next step of the process.

After the pattern of pedestals 200' is formed, a layer of material2 210 is uniformly deposited onto the exposed
25 horizontal and vertical surfaces of the first geometric pattern 200' as illustrated in Figure 2D. Such a deposition can be done by Chemical Vapor Deposition (CVD) techniques commonly used in semiconductor processing. The layer of material2 210 surrounds the pattern 200' and is also
30 deposited there between in the spaces 209'.

After depositing the material2 layer 210, a selective etch can be used to etch away its horizontal portions to the top of the pattern 200' and in the spaces 209' down to the supporting material 201. The selective etch only etches
5 vertically the exposed horizontal portions of the material2 layer 210. A Reactive Ion Etch (RIE) utilized in semiconductor manufacturing processes is used to perform the selective etching or vertical etching of horizontal surfaces. This results in leaving patterned sidewalls 210' of material2
10 intact surrounding the patterned pedestals 200' of material1 as illustrated by the cross sections 210A' and 210B' in Figure 2E. Each of the cross sections 210A' and 210B' have a width (W2) and a space 212 between them.

Referring now to Figure 2F, after forming the sidewalls
15 210', another etch is used to etch away the patterned pedestals 200' of material1. This results in the sidewalls 210' having spaces 214 between their cross sections 210A' and 210B' as well as spaces 212. This etching step may be a "wet" etch as is used in the semiconductor manufacturing
20 processes. If the material1 of the patterned pedestals 200' is a silicon oxide, the etching step can be a Buffered Oxide Etch (BOE), essentially a bath of diluted hydrofluoric acid and ammonium fluoride. Appropriately selected dry etches may
25 width W2 and spacing 212 and 214 there-between, no further division of the initial pitch is required at this point. In one embodiment the width W2 is 0.25 um while in another embodiment the width W2 is 0.1 um. With the desired feature size of the patterned sidewalls 210' achieved, the substrate
30 or support surface 201 can be processed.

The fine pattern of patterned sidewalls 210' can be utilized as an etch stop or mask for other etching steps of the substrate or support surface 201 or other material layers during semiconductor processing. In this case, sidewalls
5 protect the material layers under the sidewalls from being etched during the etching of the material around the plurality of sidewalls. Alternatively, the fine pattern of patterned sidewalls 210' can be utilized as a diffusion barrier to further diffusion steps of the substrate or
10 support surface 201 or other material layers during semiconductor processing. In this case, the sidewalls protect the material under the sidewalls from receiving the dopant when further diffusion steps of a dopant occurs around the sidewalls. Furthermore, the fine pattern of patterned
15 sidewalls 210' can be utilized as both an etch stop and a diffusion barrier in further processing steps. That is, the pattern of sidewalls 210' can act as a mask layer including an etch mask for further etch processing or a diffusion mask for further diffusion of dopants into other materials.
20 Alternatively, the pattern of sidewalls 210' are a starting pillar for structure to be formed using semiconductor processing steps.

The invention will now be illustrated using a semiconductor diode device formed out of a semiconductor
25 transistor device with a diode connection. A semiconductor diode is formed out of a vertical and cylindrical shaped junction field effect transistor (JFET) having a diode connected configuration. A vertical and cylindrical shaped junction field effect transistor (JFET) having a diode
30 connected configuration is referred to herein as a diode

configured vertical junction field effect device (JFED). The diode configured vertical JFED provides a higher channel density and can be formed using a simpler manufacturing process. The higher channel density allows a semiconductor diode to be formed in an area of silicon approximately one third of that of prior semiconductor diodes having similar performance. The higher channel density provides a considerable cost and performance advantage.

A process for fabricating embodiments of the diode configured vertical junction field effect device (JFED) are presented herein in relation to the cross-sectional views of Figures 3A-3F and Figures 4A-4I. The process forms the diode configured vertical junction field effect device (JFED). The diode configured vertical junction field effect device (JFED) can be essentially thought of as a cylindrical and vertical junction field effect transistor being diode connected with common gate and drain connections. The diode configured vertical junction field effect device may also be referred to as a vertical JFED diode. However, a diode configured vertical junction field effect device (JFED) is not a traditional junction field effect transistor (JFET) because it operates differently and is formed by a different process.

Referring now to Figures 3A-3F, cross-sectional views of steps to an exemplary process for fabricating a diode connected vertical junction field effect device are illustrated. The diode connected or diode configured vertical JFED is formed using cylindrical pedestals. Figures 3A-3F show only a portion of a wafer. It being understood that similar processing is performed across larger portions

or an entire semiconductor wafer forming more diode configured vertical JFEDs than illustrated.

Figure 3A shows a starting substrate 300 of a wafer. The substrate 300 can be silicon, gallium-arsenide (GaAs), germanium, silicon-carbide (SiC), or other known semiconductor substrate. In one embodiment, the substrate 300 is a silicon substrate having a silicon epitaxial layer therein. The silicon epitaxial layer is provided in order to form an increased reverse bias breakdown voltage for diode devices. In one embodiment, the silicon epitaxial layer has a resistivity of approximately 1.1 ohm-cm and a thickness of approximately 3um in order to achieve a reverse bias breakdown voltage of about forty-five volts. Epitaxial wafers having the silicon epitaxial layer can be purchased as starting material, or formed as part of the processing of the diode using well known standard epitaxial growth techniques.

In the case of an N-type silicon substrate, the lower or backside surface of the substrate 300 forms the cathode while a portion of the top surface of the substrate 300 is formed to be the anode. In the case of a P-type silicon substrate, the diode terminals are reversed and the lower or backside surface of the substrate 300 forms the anode while a portion of the top surface of the substrate 300 is formed to be the anode.

A thin oxide 302 is grown on the surface of the substrate 300 in order to randomize sheet implants which are to follow. The thin oxide 302 is typically one hundred fifty Angstroms (150Å) in thickness. Both of the sheet implants that follow require no masking by a mask but rather are ions that are implanted over the entire wafer.

The first sheet implant is to provide a good ohmic contact for the Anode region of the vertical JFED diode. The first sheet implant is an Arsenic implant at about 3×10^{15} atoms per cm^2 with an energy of 25 KeV. The second sheet
5 implant is a Phosphorous implant at about 2.0×10^{13} atoms per cm^2 implanted with an energy of 85 KeV. The second sheet implant sets the "threshold" or pinch off voltage of the vertical JFED diode similar to that of a JFET.

Referring now to Figure 3B, completion of a first
10 masking step is illustrated. Prior to the first masking step and etching, a layer of polysilicon is applied on top of the thin oxide 302 across the wafer. The polysilicon layer is then patterned using a mask and areas are etched away to form cylindrical shaped construction pedestals 304 on top of the
15 thin oxide 302. The cylindrical shaped construction pedestals 304 are approximately 0.1 microns (μm) high in one embodiment. The shape of the pedestals 304 can be any cylindrical shape, including but not limited to, circular, hexagonal, square, rectangular, as well as other solid shapes
20 such as serpentine, etc. For ease of description herein, the cylindrical shape will be presumptively rectangular forming rectangular cylindrical pedestals or bars formed out of the polysilicon layer.

Figure 3B illustrates a cross-section of four of a
25 plurality of rectangular cylindrical pedestals 304 that are formed across the silicon wafer. The dimensions of the rectangular cylindrical construction pedestals 304 in one embodiment are approximately 0.15 microns in width, approximately 0.1 microns in height, with a pitch of
30 approximately 0.4 microns. It is understood that these

dimensions can be altered in coordination with any adjustment in the implantation levels in order to provide similar device physics for a diode configured vertical JFED. Region 310 of silicon wafer is exploded into Figure 3C in order to further
5 detail the processing around each of the plurality of pedestals 304.

The pattern of pedestals 304 can be utilized as an etch stop for other etching steps of the oxide layer 302, the substrate 300, other material layers, or a combination
10 thereof during semiconductor processing. Alternatively, the pattern of pedestals 304 can be utilized as a diffusion barrier to further diffusion steps of the substrate 300, other material layers, or a combination thereof during semiconductor processing.

Referring now to Figure 3C, an exploded view of region 310 of Figure 3B is illustrated. The rectangular cylindrical construction pedestal 304 is formed on the surface of the thin oxide 302 on the substrate 300. Figures 3D-3F
15 illustrate the further processing of the diode configured vertical JFED with respect to the rectangular cylindrical construction pedestal 304 of Figure 3C. It is understood that similar processing occurs around each of the plurality of cylindrical construction pedestals 304.
20

Referring now to Figure 3D, the thin oxide 302 around the pedestal 304 and a portion of the pedestal 304 and the substrate 300 have been etched away forming silicon trenches 308 and substrate pedestals 309. In this case, the pattern of pedestals 304 was utilized as an etch stop for etching
25 both the oxide layer 302 and the substrate 300. The silicon trenches 308 are around the cylindrical construction
30

pedestals 304, the substrate pedestals 309, and oxide disks 302'. The oxide disks 302' are cylindrical disk shaped portions of oxide material of the thin oxide 302 which is sandwiched between the cylindrical construction pedestals 304 and the substrate pedestals 309. The substrate pedestals 309 are cylindrically shaped similar to the construction pedestals 304 but are formed out of the substrate material 300 as opposed to polysilicon material. The cylindrical substrate pedestals 309 have a cylindrical top and a cylindrical side or sides depending upon their cylindrical shape. This etch step is a Reactive Ion Etch (RIE) commonly used in silicon processing to form trench metal-oxide-semiconductor (MOS) transistors and capacitors. The depth of the etch into the substrate 300, which is not critical, is approximately 0.1 microns in one embodiment. The depth of the etch into the substrate 300 forming the depth of the silicon trenches 308, preferably corresponds to the depth of the selected energy of the Phosphorous sheet implant step previously described. The depth of the etch provides adequate threshold or pinch off control of the diode configured vertical JFED.

Referring now to Figure 3E to illustrate the next step in the process, a boron implantation 310 is performed at the base of the substrate pedestals 309 which penetrates into the silicon substrate 300. In this case, the pattern of pedestals 304 is utilized as a diffusion barrier to keep the oxide disks 302' and the substrate pedestals 309 from receiving dopant ions during diffusion. The boron implant diffuses laterally under the substrate pedestals 309, due to scattering and rapid thermal processing (RTP) for activation,

and forms a diffusion ring around a center line of the pedestals 304 and 309 referred to as a gate 312. The diffusion ring of the gate 312 has a hollow cylindrical shape which encloses a vertical channel portion 318 of the substrate 300. The vertical channel portion of the substrate 300 is cylindrically shaped around the center line of the pedestals 309 and may also be referred to as a cylindrical substrate channel. This boron implant 310 (i) provides adequate surface concentration to assure an ohmic contact to metalization; (ii) provides a P-Type surface concentration to support a breakdown voltage depletion region; and (iii) laterally diffuses to provide a JFET equivalent gate to pinch off the current flow in the vertical channel between the Anode (Top silicon surface of the pedestal formed in Fig. 3.) and the Cathode (Silicon wafer backside) during operation of each diode configured vertical JFED.

Referring now to Figure 3F, the final steps in the process of forming the diode configured vertical JFED 320 are illustrated where the remaining portions of the pedestals 304 and the disk shaped portions of the thin oxide 302 are removed and a metalization layer 314 added. An oxide etch is used to remove the oxide forming the oxide disks 302' and undercut the pedestals 304 in order to float or lift off any of their residual polysilicon material prior to metalization. A conductive layer 314, preferably a metal, is then deposited across the wafer making contact to the exposed top surfaces of the substrate 300. The conductor 314 makes contact to the diffusion ring of the P-type gate 312 and a cylindrical top surface 316 and a cylindrical side surface or surfaces of the substrate pedestals 309. The cylindrical top surface 316 and

cylindrical side surfaces of the substrate pedestals 309, but for the P-type diffusion ring of the gate, function similar to a drain or source region of a JFET. The bottom surface of the substrate 300 functions similar to a source or drain region respectively of a JFET. Note that the definition of source and drain swaps based on voltage biasing across the diode terminals. The conductor 314 contacting the diffusion ring of the gate 312 and the top surface 316 and the side surfaces of the substrate pedestals 309 provides a connection there-between to provide the diode configuration of the diode configured vertical JFED. In the case of the substrate 300 being an N-type of silicon and the gate 312 being P-type diffusion, the top surface 316 contact forms the anode of the diode. Alternatively if the substrate 300 is P-type silicon and the gate 312 being N-type diffusion, the top surface contact 316 forms the cathode. In the diode configured vertical JFED, there is little current flow from the side surfaces of the substrate pedestals 309 so that this contact area is largely non-functional. A majority of the current flow is through the top surface 316 of the substrate pedestals 309 when forward biased. From the top surface 316, the current flows through the center vertical cylindrical channel 318 of each diode configured vertical JFED 320 in a bottom portion and towards a bottom surface 319 of the substrate 300. A metal layer may optionally be applied to the bottom surface 319 of the substrate 300 or the bottom surface 319 may otherwise make contact to a conductive surface for forming a connection of the diode through which current may flow. The diode configured vertical JFEDs 320 can also be formed in a tub of silicon (equivalent to substrate 300) within an integrated circuit substrate and a

top side surface contact can be made to the tub so that the current in the bottom portion of the tub is drawn from the bottom of the channel to the top side surface contacts. Forming the vertical JFEDs in this manner allows integration
5 with other circuitry into an integrated circuit device.

While the pattern of pedestals 304 has been described as first being utilized as an etch stop and then utilized as a diffusion barrier, the order may be reversed in other semiconductor processes such that the pedestals 304 are first
10 utilized as a diffusion barrier and then utilized as an etch stop.

Referring now to Figures 4A-4I, cross-sectional views of steps to another exemplary process for fabricating the diode connected vertical junction field effect device of are
15 illustrated. The steps of forming the diode configured vertical JFED 320 illustrated in Figures 4A-4I is similar to that of the steps illustrated in Figures 3A-3F but that pedestals (previously referred to as sidewalls) are formed by using the steps described and illustrated with respect to
20 Figures 2A-2F.

Figures 4A-4I show only a portion of a wafer. It being understood that similar processing may be performed across larger portions or an entire semiconductor wafer forming more diode configured vertical JFEDs than illustrated.

25 Figure 4A shows a starting substrate 300 of a wafer. The substrate 300 can be silicon, gallium-arsenide (GaAs), germanium, silicon-carbide (SiC), or other known semiconductor substrate. In one embodiment, the substrate 300 is a silicon substrate having a silicon epitaxial layer
30 therein. The silicon epitaxial layer is provided in order to

form an increased reverse bias breakdown voltage for diode devices. In one embodiment, the silicon epitaxial layer has a resistivity of approximately 1.1 ohm-cm and a thickness of approximately 3um in order to achieve a reverse bias

5 breakdown voltage of about forty-five volts. Epitaxial wafers having the silicon epitaxial layer can be purchased as starting material, or formed as part of the processing of the diode using well known standard epitaxial growth techniques.

10 In the case of an N-type silicon substrate, the lower or backside surface of the substrate 300 forms the cathode while a portion of the top surface of the substrate 300 is formed to be the anode. In the case of a P-type silicon substrate, the diode terminals are reversed and the lower or backside surface of the substrate 300 forms the anode while a portion
15 of the top surface of the substrate 300 is formed to be the anode.

Referring now to Figure 4B, a thin oxide 302 is grown on the surface of the substrate 300 in order to randomize sheet implants which are to follow. The thin oxide 302 is
20 typically one hundred fifty Angstroms (150Å) in thickness. Both of the sheet implants that follow require no masking by a mask but rather are ions that are implanted over the entire wafer.

The first sheet implant is to provide a good ohmic
25 contact for the Anode region of the vertical JFED diode. The first sheet implant is an Arsenic implant at about 3×10^{15} atoms per cm^2 with an energy of 25 KeV. The second sheet implant is a Phosphorous implant at about 2.0×10^{13} atoms per cm^2 implanted with an energy of 85 KeV. The second sheet

implant sets the "threshold" or pinch off voltage of the vertical JFED diode similar to that of a JFET.

Then a layer of polysilicon is applied on top of the thin oxide 302 across the wafer. The polysilicon layer is
5 then patterned using a mask and areas are etched away to form cylindrical shaped construction pedestals 404 on top of the thin oxide 302.

Referring now to Figure 4C, initial construction pedestals 404 are formed on top of the thin oxide 302 by
10 completion of a first masking step. The initial construction pedestals 404 are formed of a material other than polysilicon which is used to form the second pedestals. The cylindrical shaped construction pedestals 404 may be approximately 0.1 microns (μm) high in one embodiment. The shape of the
15 pedestals 404 can be any cylindrical shape, including but not limited to, circular, hexagonal, square, rectangular, as well as other solid shapes such as serpentine, etc. For ease of description herein, the cylindrical shape will be presumptively rectangular forming rectangular cylindrical
20 pedestals or bars formed out of the polysilicon layer.

Referring now to Figure 4D, sidewalls 304', a second pedestal of material, are formed around the initial construction pedestals 404 as described with reference to Figures 2A-2F.

25 Referring now to Figure 4E, the initial construction pedestals 404 and portions of the thin oxide 302 there-under are etched away as illustrated leaving the sidewalls 304' resting on top of oxide cylinders 302'. The region 410 is magnified into Figure 4F as illustrated.

The pattern of sidewalls 304' can be utilized as an etch stop for other etching steps of the oxide layer 302, the substrate 300, other material layers, or a combination thereof during semiconductor processing. Alternatively, the pattern of sidewalls 304' can be utilized as a diffusion barrier to further diffusion steps of the substrate 300, other material layers, or a combination thereof during semiconductor processing.

Referring now to Figure 4G, the next step in the process is to etch away exposed portions of the substrate 300 to form the silicon trenches 308' around the sidewalls 304' and the substrate pedestals 309' under the sidewalls 304'. In this case, the pattern of sidewalls 304' was utilized as an etch stop for etching the substrate 300.

The process steps illustrated by Figures 4H and 4I are similar to those described previously with reference to Figures 3E and 3F to form the diode configured vertical JFET 320.

Referring now to Figure 4H to illustrate the next step in the process, a boron implantation 310 is performed at the base of the substrate pedestals 309' which penetrates into the silicon substrate 300. In this case, the pattern of sidewalls 304' is utilized as a diffusion barrier to keep the oxide disks 302' and the substrate pedestals 309' from receiving dopant ions during diffusion. The boron implant diffuses laterally under the substrate pedestals 309', due to scattering and rapid thermal processing (RTP) for activation, and forms a diffusion ring around a center line of the sidewalls 304' and substrate pedestals 309' referred to as a gate 312. The diffusion ring of the gate 312 has a hollow

cylindrical shape which encloses a vertical channel portion 318 of the substrate 300. The vertical channel portion of the substrate 300 is cylindrically shaped around the center line of the substrate pedestals 309' and may also be referred to as a cylindrical substrate channel.

Referring now to Figure 4I, the final steps in the process of forming the diode configured vertical JFED 320 are illustrated where the remaining portions of the sidewalls 304' and the disk shaped portions of the thin oxide 302' are removed and a metalization layer 314 added. An oxide etch is used to remove the oxide forming the oxide disks 302' and undercut the sidewalls 304' in order to float or lift off any of their residual polysilicon material prior to metalization. A conductive layer 314, preferably a metal, is then deposited across the wafer making contact to the exposed top surfaces of the substrate 300. A metal layer may optionally be applied to the bottom surface 319 of the substrate 300 or the bottom surface 319 may otherwise make contact to a conductive surface for forming a connection of the diode through which current may flow.

While the pattern of sidewalls 304' has been described as first being utilized as an etch stop and then utilized as a diffusion barrier, the order may be reversed in other semiconductor processes such that the sidewalls 304' are first utilized as a diffusion barrier and then utilized as an etch stop.

Referring now to Figure 5, a cross-section of a series of four diode configured vertical JFEDs 320A-D are illustrated. The metal 314 can connect a plurality of diode

configured vertical JFEDs together to provide a desired current carrying capacity.

Referring now to Figures 6A-6C, top views of exemplary arrays of diode configured vertical JFEDs are illustrated.

5 In Figure 6A, the diode configured vertical JFEDs 320 are formed using circular cylindrical pedestals (sidewalls). In Figure 6B, the diode configured vertical JFEDs 320 are formed using rectangular or square cylindrical pedestals (sidewalls). In Figure 6C, the diode configured vertical
10 JFEDs 320 are formed using hexagonal cylindrical pedestals (sidewalls). Other cylindrical shapes can be used for the pedestals (sidewalls) 304 and 304' in order to form different shapes of the diode configured vertical JFEDs 320.

15 The process steps in Figures 3A-3F and 4A-4I are described as where the diffusion ring of the gate 312 is P+ type diffusion and substrate 300 is an N type of substrate. In this case, Figure 7A illustrates the equivalent circuit of the two dimensional cross section of the diode configured vertical JFED 320. The cross-section is represented by
20 transistors 701 and 702, each representing one vertical transistor, and are n channel JFET transistors with the first terminal, T1, being the anode and the second terminal, T2, being the cathode. Figure 7B illustrates the diode equivalent of the two dimensional circuit of Figure 7A where
25 two diodes 701' and 702' are connected in parallel together. Figure 7C illustrates the electrical equivalent, a single diode 720, of the three dimensional diode configured vertical JFED 320.

30 While the process steps in Figures 3A-3F and 4A-4I are described as where the diffusion ring of the gate 312 is P+

type diffusion and substrate 300 is an N type of substrate, they may be altered by using different starting materials and different implant or dopant materials. In this case the diffusion types are reversed from n to p and from p to n in the process steps previously described. Figure 8A illustrates the equivalent circuit of the two dimensional cross section of the diode configured vertical JFED 320 illustrated in Figure 3F with reversed type of silicon diffusion and materials. In this case, the diffusion ring of the gate 312 is N+ type diffusion and substrate 300 is a P type of substrate. In Figure 8A, the transistors 801 and 802, each representing one vertical transistor, are p channel JFET transistors and the first terminal, T1, is the cathode and the second terminal, T2, is the anode. Figure 8B illustrates the diode equivalent of the two dimensional circuit of Figure 8A where two diodes 801' and 802' are connected in parallel together. Figure 8C illustrates the electrical equivalent, a single diode 820, of the three dimensional diode configured vertical JFED with altered material types.

Referring now to Figure 9, a plurality of diode active areas 90 are separated by scribe channels 91 between the diode active areas 90 on the wafer. In each diode active area 90 are a plurality of diode configured vertical JFEDs 320. Edge termination of the diode active areas in the scribe channels 91 can be provided through several semiconductor device terminations including a tapered termination or a mesa termination. Additionally, single or multiple normal ring terminations which are well known can be

used; or, voltage permitting, a simple guard ring integral with the device active diffusions can be used.

Referring now to Figure 10, the schematic equivalent of the diode active area 90 having multiple diodes 720, each
5 representing a diode configured vertical JFED 320, connected in parallel together. Adding the current capability of each of the diode configured vertical JFED devices 320 connected in parallel together results in a large current carrying capability. It is understood that there are several hundred
10 diode active areas 90 on a wafer, with only four being shown in Figure 9. Each individual diode active area 90 can contain thousands of individual diode configured vertical JFEDs 320.

With respect to the current capability of the diode, the
15 forward current is a function of the number of diode configured vertical JFEDs 320 which are coupled in parallel together.

With respect to the threshold voltage, by appropriately selecting the dopants, their concentrations, and other
20 materials and dimensions for fabrication of the diode configured vertical JFED, the channel regions may be made to just conduct at substantially zero forward bias across the anode and cathode. Thus, in true rectifying applications such as in power supplies and the like, the invention results
25 in reduced power consumption and heating in the rectifying devices, and greater overall efficiency of the resulting circuits.

With respect to the reverse bias breakdown voltage of the diode configured vertical JFED 320, a reverse bias
30 voltage appears between the gate 312 and the substrate 300

causing the channel 318 to be pinched off and a depletion region to form in the substrate 300. The electric field lines of the reverse bias voltage are substantially planar around the diode configured vertical JFET due to the longitudinal shape of the diffusion for the gate 312 and the very small dimensions of the pedestals. This planar field effect increases the reverse breakdown voltage capability. To increase the reverse bias breakdown voltage further, it is desirable to keep the electric field lines straight and parallel with little crowding at pn junctions and having a minimal amount of curvature near electric field termination points such as at device termination near the scribe lines 91.

Referring now to Figures 11A-13A and Figures 11B-13B, top views and cross-sectional side views of another embodiment for forming sidewalls in the processing of a semiconductor device are illustrated.

Referring now to Figures 11A and 11B, a substrate 301 is covered with a uniform layer 302 of material1 and a uniform layer 303 of material2. A thick layer 200 of material2 is then deposited on top of the uniform layer 303. The thick layer 200 is then patterned using a mask to form pedestals 200'. The mask has repetitive patterns of oval geometric shapes to form the oval construction pedestals 200' illustrated in Figures 11A and 11B.

Referring now to Figure 12A and 12B, sidewalls 210' of material1 are formed around the construction pedestals 200'. Between the repetitive pattern of sidewalls 210' is a space 209'. The top view as illustrated by Figure 12A, shows the

oval cylinders of the sidewalls 210' concentric with the construction pedestals 200'.

Referring now to Figures 13A and 13B, the pedestals 200' of material 2 and exposed portions of the uniform layer 303 are removed by an etching step leaving a repetitive pattern of hollow cylindrical sidewalls 210' having a cross-section of the width of the sidewall. Spaces 214 are formed therein, while spaces 209' remain between adjacent sidewalls 210'. A hollow cylindrical portion 303' of the uniform layer 303 remains intact under the hollow cylindrical sidewalls 210'. The uniform layer 302 may provide an etch stop to keep unexposed portions of the substrate 301 from being etched. However, if the pattern of sidewalls 210' has the desired pitch, further division of the initial pitch is not needed and the process can jump to processing the substrate 301 and the uniform layer 302.

Figures 14-16 are top views of alternate embodiments of geometric shapes having fine geometric dimensions of a repetitive pattern for a semiconductor device. Figure 14 illustrates a hexagonal repetitive pattern used to form fine geometries. Figure 15 illustrates a circular repetitive pattern used to form fine geometries. Figure 16 illustrates a square or rectangular repetitive pattern to form fine geometries. Each of the resultant patterns have concentric cylindrically shaped sidewalls having a cross-sectional thickness of the width and spaced apart by the spacing in order to form the final pitch.

In certain instances in the foregoing description, certain alternate materials and methods were set forth. It is to be noted however, that the identification of specific

alternative materials and processes is not to infer that still other materials and processes for those or other steps in the process of fabrication or in the resulting diode devices are excluded from use in the invention. To the

5 contrary, steps and materials other than those set out herein will be known to those skilled in the art. Thus while the invention has been disclosed and described with respect to certain preferred embodiments, it will be understood to those skilled in the art that the invention may be varied without
10 departing from the spirit and scope of thereof.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
220